BORIS PLUG&PLAY MWS SENSOR

96634059

Microwave presence sensor

Plug&Play microwave presence sensor with daylight sensor for illuminance levels between 200 and 500 lux will ensure that light is only delivered when needed. The motion detection range, the hold time as well as the standby dimming level are fully adjustable via Dial Code system or remote control. Additional features available by remote control (BORIS MWS SENSOR REMOTE CONTROL): Brightness level in operation mode. Adjustable in 10% steps from 10 - 100%. Operation as photocell by disabling presence detection. Maximum mounting height is 12m.
Weight: 0.07 kg

TE_BORIS_F_MWS_SENS_PERSP.jpg

All values marked with an * are rated values. Unless stated otherwise, the values apply to an ambient temperature of 25°C.

IEC EN 60598-1 RG 1 RoHS IP65 IK08 650°C Ta -30 +45

We reserve the right to make technical changes without prior notice. 22.06.2021 © ThornEco